

# Charminglite

## SK6812 dream color LED Strip










\*LED Chip is built in IC, then the components is less, pixels can be high, can make attractive appearance and so on.

\*IC is designed with one data line, two power lines, 256 gray scale, high brightness, fast data transfer, fast screen refresh

\*Each lamp bead forms a loop, can be arbitrarily cut according to the length of the loop, without damaging other parts

### RGB



Scissors to cut at the mouth



CE RoHS



### Application

Part No.	Voltage	Wattage	PCB Width	LED Qty/M	Cutting Intervals	Color Temp.	Light Output IP20	CRI	Standard Length
CL-6812-30-5V	5V DC	9W/M	10MM	30LEDs/M	33.08mm(5V)	RGB	N/A	N/A	5 Meters/Reel
CL-6812-60-5V	5V DC	18 W/M	10MM	60LEDs/M	16.54mm(5V)	RGB	N/A	N/A	5 Meters/Reel
CL-6812-72-5V	5V DC	21.6W/M	12MM	72LEDs/M	13.78mm(5V)	RGB	N/A	N/A	5 Meters/Reel
CL-6812-96-5V	5V DC	28.8W/M	12MM	96LEDs/M	10.33mm(5V)	RGB	N/A	N/A	5 Meters/Reel
CL-6812-144-5V	5V DC	43.2W/M	12MM	144LEDs/M	6.9mm(5V)	RGB	N/A	N/A	5 Meters/Reel